

FG 2 N	Si-Di	TV-Damper-Di, 300V, 1A	31a	BYD 33 M	31a
FJ 2501	Si-P-Darl	=BDX 34A	17j	BD 902	17j
FJ 3001	Si-N-Darl	=BDX 33A	17j	BD 901	17j
FKE 4 F2/....	Si-Di	>SKE 4F2/...	33a	SKE 4F2/10	33a
FL 005...08	Si-Br	50... 800V, 5A	33(+=====)	B380C5000	33(+=====)
FLV....	Opto			-	
FMMT 2484	Si-N	=2N2484: SMD	35a	BC 850	35a
FMMT 3903...3904	Si-N	=2N3903...3904: SMD	35a	BC 846	35a
FMMT 3905...3906	Si-P	=2N3905...3906: SMD	35a	BC 856	35a
FMMT 4124	Si-N	=2N4124: SMD	35a	BC 846	35a
FMMT 4125	Si-P	=2N4125: SMD	35a	BC 856	35a
FMMT 5087	Si-P	=2N5087: SMD	35a	BC 860	35a
FMMT 5087 R	Si-P	=2N5087: SMD	35a	-	
FMMT-A20	Si-N	=MPSA 20: SMD	35a	BC 846	35a
FMMT-A70	Si-P	=MPSA 70: SMD	35a	BC 856	35a
FMPS-A 05	Si-N	=MPSA 05	7e	·MPSA 05	
FMPS-A 06	Si-N	=MPSA 06	7e	·MPSA 06	
FMPS-A 55	Si-P	=MPSA 55	7e	·MPSA 55	
FMPS-A 56	Si-P	=MPSA 56	7e	·MPSA 56	
FPT 6004	Si-P-Darl	=BD 902	17j	BD 902	17j
FPT 6005	Si-N-Darl	=BD 901	17j	BD 901	17j
FR 1/....	Si-Di	Gl		1N4007	31a
FR 1 A...M	Si-Di	SMD, Gl, S, 50...1000V, 0,6A, <500ns	71a(5mm)	-	
FR 2/-02.....12	Si-Di	Gl, Uni, 200...1200V, 1,1A	31a	1N4007	31a
FR 2 A...M	Si-Di	SMD, Gl, S, 50...1000V, 1,5A, <500ns	71a(5mm)	-	
FR 34	Si-Di	Gl, Uni, 100V, 0,2A, Uf<1V(0,2A)	31a	BA 159	31a
FR 101	Si-Di	Gl, 50V, 1A	31a	BY 133	31a
FR 102	Si-Di	=FR 101: 100V	31a	BY 133	31a
FR 103	Si-Di	=FR 101: 200V	31a	BY 133	31a
FR 104	Si-Di	=FR 101: 400V	31a	BY 133	31a
FR 105	Si-Di	=FR 101: 600V	31a	BY 133	31a
FR 106	Si-Di	=FR 101: 800V	31a	BY 133	31a
FR 107	Si-Di	=FR 101: 1000V	31a	BY 133	31a
FR 151	Si-Di	Gl, 50V, 1,5A	31a	BYD 33 M	31a
FR 152	Si-Di	=FR 151: 100V	31a	BYD 33 M	31a
FR 153	Si-Di	=FR 151: 200V	31a	BYD 33 M	31a
FR 154	Si-Di	=FR 151: 400V	31a	BYD 33 M	31a
FR 155	Si-Di	=FR 151: 600V	31a	BYD 33 M	31a
FR 156	Si-Di	=FR 151: 800V	31a	BYD 33 M	31a
FR 157	Si-Di	=FR 151: 1000V	31a	BYD 33 M	31a
FR 301	Si-Di	Gl, 50V, 3A	31a	BY 255	31a
FR 302	Si-Di	=FR 301: 100V	31a	BY 255	31a
FR 303	Si-Di	=FR 301: 200V	31a	BY 255	31a
FR 304	Si-Di	=FR 301: 400V	31a	BY 255	31a
FR 305	Si-Di	=FR 301: 600V	31a	BY 255	31a
FR 306	Si-Di	=FR 301: 800V	31a	BY 255	31a
FR 307	Si-Di	=FR 301: 1000V	31a	BY 255	31a
FR 601	Si-Di	Gl, 50V, 6A	31a	BY 500/800	31a 7
FR 602	Si-Di	=FR 601: 100V	31a	BY 500/800	31a 7
FR 603	Si-Di	=FR 601: 200V	31a	BY 500/800	31a 7
FR 604	Si-Di	=FR 601: 400V	31a	BY 500/800	31a 7
FR 605	Si-Di	=FR 601: 600V	31a	BY 500/800	31a 7
FR 606	Si-Di	=FR 601: 800V	31a	BY 500/800	31a 7
FR 607	Si-Di	=FR 601: 1000V	31a	-	
FR 4001	Ge-Di	=AY 103K	3	-	
FR 4001 [Thomson]	Si-Di	=BYX 58/400		->BYX 58/...	