

1 N 4912(A)		Ref-Di	=1N4896: 12.8V(7.5mA), <25Ω	31a	DO-7	-	-	-	-
1 N 4913(A)		Ref-Di	=1N4912: ±0.005%/°C	31a	DO-7	-	-	-	-
1 N 4914(A)		Ref-Di	=1N4912: ±0.002%/°C	31a	DO-7	-	-	-	-
1 N 4915(A)		Ref-Di	=1N4912: ±0.001%/°C	31a	DO-7	-	-	-	-
1 N 4916(A)		Ref-Di	=1N4896: 19.2V(0.5mA), <600Ω	31a	DO-7	-	-	-	-
1 N 4917(A)		Ref-Di	=1N4916: ±0.005%/°C	31a	DO-7	-	-	-	-
1 N 4918(A)		Ref-Di	=1N4916: ±0.002%/°C	31a	DO-7	-	-	-	-
1 N 4919(A)		Ref-Di	=1N4896: 19.2V(1mA), <300Ω	31a	DO-7	-	-	-	-
1 N 4920(A)		Ref-Di	=1N4919: ±0.005%/°C	31a	DO-7	-	-	-	-
1 N 4921(A)		Ref-Di	=1N4919: ±0.002%/°C	31a	DO-7	-	-	-	-
1 N 4922(A)		Ref-Di	=1N4896: 19.2V(2mA), <150Ω	31a	DO-7	-	-	-	-
1 N 4923(A)		Ref-Di	=1N4922: ±0.005%/°C	31a	DO-7	-	-	-	-
1 N 4924(A)		Ref-Di	=1N4922: ±0.002%/°C	31a	DO-7	-	-	-	-
1 N 4925(A)		Ref-Di	=1N4896: 19.2V(4mA), <75Ω	31a	DO-7	-	-	-	-
1 N 4926(A)		Ref-Di	=1N4925: ±0.005%/°C	31a	DO-7	-	-	-	-
1 N 4927(A)		Ref-Di	=1N4925: ±0.002%/°C	31a	DO-7	-	-	-	-
1 N 4928(A)		Ref-Di	=1N4925: ±0.001%/°C	31a	DO-7	-	-	-	-
1 N 4929(A)		Ref-Di	=1N4896: 19.2V(7.5mA), <36Ω	31a	DO-7	-	-	-	-
1 N 4930(A)		Ref-Di	=1N4929: ±0.005%/°C	31a	DO-7	-	-	-	-
1 N 4931(A)		Ref-Di	=1N4929: ±0.002%/°C	31a	DO-7	-	-	-	-
1 N 4932(A)		Ref-Di	=1N4929: ±0.001%/°C	31a	DO-7	-	-	-	-
1 N 4933(GP)	USA, EUR	Si-Di	FRr, 50V, 1A, Uf<1,1V(1A), <200ns	31a	SOD-22	BYD 33 M	31a	BYT 52A, BYX 92/50, EGP 10A, RGP 10A, ++	
1 N 4934(GP)		Si-Di	=1N4933: 100V	31a	SOD-22	BYD 33 M	31a	BYT 52B, BYX 92/100, EGP 10B, RGP 10B, ++	
1 N 4935(GP)		Si-Di	=1N4933: 200V	31a	SOD-22	BYD 33 M	31a	BYT 52D, BYX 92/200, EGP 10D, RGP 10D, ++	
1 N 4936(GP)		Si-Di	=1N4933: 400V	31a	SOD-22	BYD 33 M	31a	BY 201/4, BYT 52G, BYX 92/400, RGP 10G, ++	
1 N 4937(GP)		Si-Di	=1N4933: 600V	31a	SOD-22	BYD 33 M	31a	BY 201/6, BYT 52J, BYX 92/600, RGP 10J, ++	
1 N 4938	USA, Fch, Hit	Si-Di	S, 175/200V, 0,2/0,6A, Uf<1V(0,1A), <50ns, =1N3070	31a	DO-35			*N3070	
1 N 4939	Phi	Ge-Di	UHF, Ka-Band Mx	Koax	SOD-42				
1 N 4940	Phi	Ge-Di	UHF, X-Band Mx	Koax	SOD-42				
1 N 4941	Phi	GaAs-Di	UHF Tuning	Koax	SOD-31				
1 N 4942(GP)	USA, Sie, Tho	Si-Di	FRr, 200V, 1A, Uf<1,3V(1A), <150ns	IGP: SOD-22 31a	SOD-5	BYD 33 M	31a	BYT 52D, BYX 92/200, EGP 10D, RGP 10D, ++	
1 N 4943(GP)		Si-Di	=1N4942: 300V	31a	SOD-51	BYD 33 M	31a	BYT 52G, BYX 92/300, RGP 10G, ++	
1 N 4944(GP)		Si-Di	=1N4942: 400V	31a	SOD-51	BYD 33 M	31a	BYT 52G, BYX 92/400, RGP 10G, ++	
1 N 4945(GP)		Si-Di	=1N4942: 500V	31a	SOD-51	BYD 33 M	31a	BY 201/6, BYT 52J, RGP 10J, ++	
1 N 4946(GP)		Si-Di	=1N4942: 600V, <250ns	31a	SOD-51	BYD 33 M	31a	BY 201/6, BYT 52J, RGP 10J, ++	
1 N 4947(GP)		Si-Di	=1N4942: 800V, <250ns	31a	SOD-51	BYD 33 M	31a	BYV 15...16, BYT 52K, RGP 10K, ++	
1 N 4948(GP)		Si-Di	=1N4942: 1000V, <500ns	31a	SOD-51	BYD 33 M	31a	BYV 16, BYV 38, BYT 52M, RGP 10M, ++	
1 N 4949	ldc, Inr	Si-Di	SS, 35V, <0,3ns	31a	DO-7				
1 N 4950	USA	Si-Di	SS, 30V, <4ns	31a	DO-7				BA 218, BAX 13, BAX 91, 1N4148...49, ++
1 N 4951	Gen	Si-Di	Dual, TV HA Sync. 20V, 25mA, Uf<0,85V(1mA)	7e	TO-98	(2x1N4148)	31a		
1 N 4952	Gen	Si-Di	=1N4951: 50V	7e	TO-98	(2x1N4148)	31a		
1 N 4953	Hew	-Di	SS, 30V	Koax	SOD-31				
1 N 4954	USA	Z-Di	6.8V, 5%, 5W	31a	SOD-51				BZV 40/..., BZV 48/..., 1N5342...5388
1 N 4955		Z-Di	=1N4954: 7.5V	31a	SOD-51				
1 N 4956		Z-Di	=1N4954: 8.2V	31a	SOD-51				
1 N 4957		Z-Di	=1N4954: 9.1V	31a	SOD-51				
1 N 4958		Z-Di	=1N4954: 10V	31a	SOD-51				
1 N 4959		Z-Di	=1N4954: 11V	31a	SOD-51				
1 N 4960		Z-Di	=1N4954: 12V	31a	SOD-51				
1 N 4961		Z-Di	=1N4954: 13V	31a	SOD-51				
1 N 4962		Z-Di	=1N4954: 15V	31a	SOD-51				
1 N 4963		Z-Di	=1N4954: 16V	31a	SOD-51				
1 N 4964		Z-Di	=1N4954: 18V	31a	SOD-51				
1 N 4965		Z-Di	=1N4954: 20V	31a	SOD-51				
1 N 4966		Z-Di	=1N4954: 22V	31a	SOD-51				
1 N 4967		Z-Di	=1N4954: 24V	31a	SOD-51				
1 N 4968		Z-Di	=1N4954: 27V	31a	SOD-51				
1 N 4969		Z-Di	=1N4954: 30V	31a	SOD-51				
1 N 4970		Z-Di	=1N4954: 33V	31a	SOD-51				
1 N 4971		Z-Di	=1N4954: 36V	31a	SOD-51				
1 N 4972		Z-Di	=1N4954: 39V	31a	SOD-51				
1 N 4973		Z-Di	=1N4954: 43V	31a	SOD-51				
1 N 4974		Z-Di	=1N4954: 47V	31a	SOD-51				
1 N 4975		Z-Di	=1N4954: 51V	31a	SOD-51				
1 N 4976		Z-Di	=1N4954: 56V	31a	SOD-51				
1 N 4977		Z-Di	=1N4954: 62V	31a	SOD-51				
1 N 4978		Z-Di	=1N4954: 68V	31a	SOD-51				
1 N 4979		Z-Di	=1N4954: 75V	31a	SOD-51				
1 N 4980		Z-Di	=1N4954: 82V	31a	SOD-51				
1 N 4981		Z-Di	=1N4954: 91V	31a	SOD-51				
1 N 4982		Z-Di	=1N4954: 100V	31a	SOD-51				
1 N 4983		Z-Di	=1N4954: 110V	31a	SOD-51				
1 N 4984		Z-Di	=1N4954: 120V	31a	SOD-51				
1 N 4985		Z-Di	=1N4954: 130V	31a	SOD-51				
1 N 4986		Z-Di	=1N4954: 150V	31a	SOD-51				
1 N 4987		Z-Di	=1N4954: 160V	31a	SOD-51				
1 N 4988		Z-Di	=1N4954: 180V	31a	SOD-51				
1 N 4989		Z-Di	=1N4954: 200V	31a	SOD-51				
1 N 4990		Z-Di	=1N4954: 220V	31a	SOD-51				
1 N 4991		Z-Di	=1N4954: 240V	31a	SOD-51				
1 N 4992		Z-Di	=1N4954: 270V	31a	SOD-51				
1 N 4993		Z-Di	=1N4954: 300V	31a	SOD-51				
1 N 4994		Z-Di	=1N4954: 330V	31a	SOD-51				
1 N 4995		Z-Di	=1N4954: 360V	31a	SOD-51				
1 N 4996		Z-Di	=1N4954: 390V	31a	SOD-51				
1 N 4954A...4996A		Z-Di	=1N4954...4996: 10%	31a	SOD-51				
1 N 4954B...4996B		Z-Di	=1N4954...4996: 20%	31a	SOD-51				
1 N 4997(R)	USA, Mot	Si-Di	=1N4719						*1N4719
1 N 4998(R)	USA, Mot	Si-Di	=1N4720						*1N4720
1 N 4999(R)	USA, Mot	Si-Di	=1N4721						*1N4721
1 N 5000(R)	USA, Mot	Si-Di	=1N4722						*1N4722
1 N 5001(R)	USA, Mot	Si-Di	=1N4723						*1N4723
1 N 5002(R)	USA, Mot	Si-Di	=1N4724						*1N4724